Corella Multi-Arm Spider Ceiling Light

Installation Guide



In the box

Stem with arms and shades (3 or 6) · ceiling canopy · cross bracket and screws · terminal block · LED globes

You will need

Drill, screwdriver, pencil and stepladder. A helper for the 6-light. LED globes are included; when replacing one, use the same type as the globe supplied. The arms sit 30 cm below the ceiling.

Important safety information

- This light must be installed by a licensed electrician, in line with AS/NZS 3000 (Wiring Rules) and local regulations.
- Turn the power off at the switchboard before installing, cleaning or servicing the light.
- Use screws and wall plugs suited to your wall (plasterboard, timber or masonry).
- 6-light: ask your electrician to check the ceiling can take the fitting.
- Move the arms and shades by hand only; never force the joints.

Step by step

1. **Assemble the arms**
   Slide each arm into its socket on the stem until fully home, then tighten its fixing screw.
2. **Join the stem and canopy**
   Pass the cables up through the canopy and fix the stem to it with the nut and washer supplied.
3. **Fix the mounting bracket**
   Screw the cross-shaped bracket firmly to the ceiling, into a joist or with suitable plasterboard anchors.
4. **Connect the wiring**
   With the power OFF, connect the supply to the light through the terminal block: Active to L, Neutral to N, and Earth to the earth terminal if one is fitted.
5. **Fit the canopy**
   Tuck the wires inside the canopy and tighten the side screws into the bracket until it sits flush.
6. **Aim the arms and fit the globes**
   Rotate each arm and tilt each shade by hand, then screw the supplied LED globe into each shade.
7. **Test**
   Restore the power at the switchboard and switch on the light.

Care and cleaning

Turn the light off and let it cool. Dust the arms and shades with a soft, dry cloth. Avoid water and cleaning sprays.

Need help?

Email hello@aussielights.com with your order number and a photo. Your light is covered by our 2-year warranty and 30-day returns.