Kade Concrete & Mesh Pendant Light

Installation Guide

In the box

1 x cement top with lampholder and black mesh shade · 120 cm adjustable cable · canopy with bracket · fixing hardware

You will need

Drill, screwdriver, wire cutters, pencil and stepladder. One ES (E27) globe, max 40 W, sold separately (warm 2200 to 2700K filament LED recommended).

Important safety information

- This light must be installed by a licensed electrician, in line with AS/NZS 3000 (Wiring Rules) and local regulations.
- Turn the power off at the switchboard before installing, cleaning or servicing the light.
- Use screws and wall plugs suited to your wall (plasterboard, timber or masonry).
- Fix the bracket to a ceiling joist or solid support able to hold twice the light's weight. Only connect power once fully assembled.
- Max 40 W. Keep the cable away from cots, and curtains clear of the globe. Small air holes in the hand-cast cement are normal.

Step by step

1. **Power off**
   Switch off the circuit at the switchboard before starting.
2. **Fix the bracket**
   Separate the canopy from its bracket. Mark the holes and screw the bracket firmly into a ceiling joist or a solid support.
3. **Set the drop**
   Adjust the cable to the height you want and cut any excess, leaving enough length to connect.
4. **Connect the wiring**
   Connect the light to the supply: Active to L, Neutral to N, and Earth to the earth terminal if one is fitted. Check every connection is tight.
5. **Fit the canopy**
   Tuck the wires neatly inside, then fit the canopy over the bracket and secure it flush with the ceiling.
6. **Fit the globe and test**
   Reach inside the mesh shade, screw in an ES (E27) globe of max 40 W, then restore the power and switch on.

Care and cleaning

Switch off and let the globe cool before touching or replacing it. Dust the cement and mesh with a soft, dry cloth only: no water, chemical solvents or abrasive cleaners.

Need help?

Email hello@aussielights.com with your order number and a photo. Your light is covered by our 2-year warranty and 30-day returns.