Foundry Black Cone Industrial Pendant Light

Installation Guide



In the box

1, 2 or 3 pendants with black shade and brass-tone lampholder (per style) · ceiling canopy with mounting bracket (one per pendant, or one bar or round plate for the 3-light styles) · fixing hardware

You will need

Drill, screwdriver, pencil and stepladder. One ES (E27) globe per shade, max. 40 W, sold separately (warm white LED, 2700 to 3000K, recommended). Leave 70 to 80 cm between the shades and your benchtop.

Important safety information

- This light must be installed by a licensed electrician, in line with AS/NZS 3000 (Wiring Rules) and local regulations.
- Turn the power off at the switchboard before installing, cleaning or servicing the light.
- Use screws and wall plugs suited to your wall (plasterboard, timber or masonry).
- Set of 2 or 3: each pendant needs its own ceiling point. Repeat the steps for each pendant.

Step by step

1. **Fix the mounting bracket**
   Separate the canopy from its bracket. Mark the holes and fix the bracket firmly to the ceiling, into a joist or with suitable plasterboard anchors.
2. **Set the drop**
   Adjust each pendant's cable to the height you want (up to 100 cm) and lock it in place: level for a bar, staggered for a cluster. Your electrician can trim any extra cable.
3. **Connect the wiring**
   With the power OFF, connect the pendant cable(s) to the supply: Active to L, Neutral to N, and Earth to the earth terminal if one is fitted.
4. **Fit the canopy**
   Push the canopy up over the bracket, tuck the wires neatly inside and secure it so it sits flush with the ceiling.
5. **Fit the globes**
   Screw one ES (E27) globe, no higher than 40 W, into each lampholder, gently and without force.
6. **Test**
   Restore the power at the switchboard and switch on the light.

Care and cleaning

Turn the light off and let it cool. Dust the shades and lampholders with a soft, dry cloth. Do not use water, solvents or abrasive cleaners.

Need help?

Email hello@aussielights.com with your order number and a photo. Your light is covered by our 2-year warranty and 30-day returns.