Hugo Climbing Man Pendant Light

Installation Guide

In the box

Single: 1 x climbing figure (40 x 26 cm) with lampholder, 100 cm adjustable cable, ceiling canopy (Ø 10 cm) with bracket · 3-light: 3 figures with 100 cm adjustable cables, round canopy or 50 cm linear bar with bracket · fixing hardware

You will need

Drill, screwdriver, wire cutters, pencil and stepladder. One ES (E27) globe per figure, sold separately (a small round warm white LED globe, 2700 to 3000K, is recommended).

Important safety information

- This light must be installed by a licensed electrician, in line with AS/NZS 3000 (Wiring Rules) and local regulations.
- Turn the power off at the switchboard before installing, cleaning or servicing the light.
- Use screws and wall plugs suited to your wall (plasterboard, timber or masonry).
- Fix the bracket to a ceiling joist or solid support, not to plasterboard alone.
- On the 3-light versions, set each cable to a different length for the staggered look in our photos.

Step by step

1. **Power off**
   Switch off the circuit at the switchboard before starting.
2. **Fix the bracket**
   Separate the canopy or bar from its bracket. Mark the holes and screw the bracket firmly into a ceiling joist or a solid support.
3. **Set the drops**
   Adjust each cable to the height you want and cut any excess, leaving enough length to connect.
4. **Connect the wiring**
   Connect the light to the supply: Active to L, Neutral to N, and Earth to the earth terminal if one is fitted. On 3-light versions, join the three cables to the supply inside the canopy or bar.
5. **Fit the canopy**
   Tuck the wires neatly inside, then fit the canopy or bar over the bracket and secure it flush with the ceiling.
6. **Fit the globes and test**
   Screw an ES (E27) globe into each figure's lampholder, then restore the power and switch on.

Care and cleaning

Switch off and let the globes cool first. Dust the metal with a soft, dry cloth and avoid water or harsh cleaners.

Need help?

Email hello@aussielights.com with your order number and a photo. Your light is covered by our 2-year warranty and 30-day returns.