Mika 23cm Colourful Mushroom Pendant Light

Installation Guide



In the box

1 x metal mushroom shade with ES (E27) lampholder · 1 x ceiling canopy with mounting bracket · adjustable cable · screws and wall plugs

You will need

Drill, screwdriver, pencil and stepladder. One ES (E27) globe, sold separately (warm white LED, 2700 to 3000K, recommended). Hang the shade about 75 cm above a table or bench (70 to 80 cm over an island).

Important safety information

- This light must be installed by a licensed electrician, in line with AS/NZS 3000 (Wiring Rules) and local regulations.
- Turn the power off at the switchboard before installing, cleaning or servicing the light.
- Use screws and wall plugs suited to your wall (plasterboard, timber or masonry).
- Use an LED globe and do not exceed the maximum wattage shown on the lampholder.
- Handle the glossy shade with a soft cloth to avoid marks and scratches.

Step by step

1. **Fix the mounting bracket**
   Separate the canopy from its bracket. Mark the holes and fix the bracket firmly to the ceiling, into a joist or with suitable plasterboard anchors.
2. **Set the drop**
   Loosen the cable grip at the canopy, set the drop you want, up to 100 cm, and tighten the grip. Your electrician can trim any extra cable.
3. **Connect the wiring**
   With the power OFF, connect the cable to the supply: Active to L, Neutral to N, and Earth to the earth terminal if one is fitted.
4. **Fit the canopy**
   Push the canopy up over the bracket, tuck the wires neatly inside and tighten the screws until it sits flush with the ceiling.
5. **Fit the globe**
   Screw an ES (E27) globe into the lampholder, gently and without force.
6. **Test**
   Restore the power at the switchboard and switch on the light.

Care and cleaning

Turn the light off and let it cool. Dust the shade with a soft, dry cloth. Do not use solvents or abrasive cleaners; never wet the lampholder or the cable.

Need help?

Email hello@aussielights.com with your order number and a photo. Your light is covered by our 2-year warranty and 30-day returns.